

Energizer Vision HD Ultra Digital Focus

PMZH611



The *Energizer*® VISION HD Ultra with Digital Focus delivers high-performance innovation with an exceptional light output brightness and hours of runtime. The *Energizer* patented Digital Focus technology allows consumers to choose their optimal array of light between focused and area light by simply pressing the light switch. Unique MAXVIZ technology enables users to experience sharp, high-definition performance with daylight color and wide, uniform light output. This new light is our brightness light with 1500 Lumens and with its aircraft grade aluminum, it delivers exceptional quality and durability. The *Energizer* Vision HD Ultra is dependable and perfect for indoor situations such as DIY project and power outages, as well as outdoor activities such as camping.

Lumens	Runtime	Beam Distance	Drop	Water Ingress
<p>FL1 STANDARD 1500 LUMENS</p>	<p>FL1 STANDARD 4h</p>	<p>FL1 STANDARD 230m</p>	<p>FL1 STANDARD 1m</p>	<p>FL1 STANDARD IPX4</p>



DESIGN BENEFITS

- ✓ Durable Aircraft Grade Aluminum
- ✓ One handed focusing operation: Digital Focus
- ✓ Versatility: multiple modes
- ✓ 20 Years Design to Last based on typical consumer usage patterns
- ✓ Strobe mode: Press 3 times to activate strobe
- ✓ Shatterproof Lens

PERFORMANCE BENEFITS

- ✓ Up to 15X Brighter than Standard LED Technology
- ✓ Long Run Time
- ✓ MAXVIZ Technology to deliver a wide, powerful beam and high-definition vision

LIGHT AND POWER SOURCE

- ✓ Features LED Technology
- ✓ 4.25 Hz strobe light
- ✓ Operates on 6 AA Batteries

PRODUCT SPECIFICATIONS

Weight:	278 Grams / 9.81 Ounces
Dimensions:	226 mm x 48 mm x 35 mm 8.88" x 1.88" x 1.38"

ELECTRICAL CHARACTERISTICS

Nominal Power Consumption:	11.4 W
Batteries:	6 AA Energizer E91 4.5V dc
LED Specifications:	LED 3.0V cc / 3800 mA

DISCLAIMERS

Tested according to ANSI FL1 Standards.
 This device complies with part 15 of the FCC Rules.
 Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

CERTIFICATES AND COMPLIANCE

EMC, EN62471, FCC



Publish Date: 09-06-2022

BATTERY SPECIFICATIONS

Battery Type	Energizer Max Alkaline
Battery Size	AA
Number of Cells	6

BATTERY PERFORMANCE

Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	1500	4	230
Low	250	15	-
Strobe	-	-	-

Spot High	Digital Focus
Spot Low	
Wide High	
Wide Low	

Modes

High, Low, Strobe, Spot High, Spot Low, Wide High, Wide Low

OPERATING INSTRUCTIONS

1. Press on/off button to turn on.
2. Press 1X for High.
3. Press 2X for Low.
4. Press and hold in either mode for digital focus (Spot/Wide).
5. Press 3X for strobe.
6. In any mode next press will be off.

BATTERY CHANGING INSTRUCTIONS

1. Batteries (6X AA) are user replaceable.
2. Unscrew tail cap and insert batteries according to instruction printed on tail cap. Re-screw tail cap back onto light.