

# **USB back-to-back extension lead**

HIGH GLOSS USB

power and charge your USB devices with sockets protected against damaging surges and spikes

#### **FEATURES**

- Two USB ports (2.1A shared)
- · Protects valuable electrical equipment from surges and spikes

POWER


- · Unlimited value, 3 year connected equipment warranty
- · LED power and surge indicators
- Compact back-to-back design
- · Wall fixing option

## **PRODUCT IMAGES**





## LINE DIAGRAMS



4

OCKET

# **PRODUCT INFORMATION**

Part Number	SRGU4xPy2
Part Number Note	x = length of cable in metres, y = colour
Product Dimensions	Height 28.5mm x Width 325mm x Depth 65mm
Sockets	4

### **TECHNICAL SPECIFICATIONS**

Standard(s)	This product is certified to applicable British safety standards	CE
	BS5733, BS EN 60950-1	
Wall Mounting Option	Yes	
Maximum Load (Wattage)	13A: 3120 Watts, 240 Volts	
IF IN DOUBT CONSULT A QUALIFIED ELECTRICIAN		

#### SURGE TECHNICAL DATA

Protection	3 x 14 MOV + 1 x GDT
Maximum Surge Energy	375 Joules
Maximum Surge Current	13500 Amps
Clamping Voltage	775 Volts
Response Time	< 10nS
Thermal Cut Out	Yes
Protection	L-N, L-E, N-E
Surge Protection Indicator	Yes - White
Power Indicator	Yes - Blue

#### **SAFETY WARNING**

PLEASE READ CAREFULLY AND USE IN ACCORDANCE WITH OUR SAFETY INSTRUCTIONS BELOW

🖌 DO 🖌 DO Uncoil cable before use

Use in wet conditions

- DON'T Position the cable carefully to avoid accidents (X) DON'T 🚺 DON'T
- Allow heavy tools etc to hang unsupported on the cable or from the socket Remove the plug and wire directly into a mains supply Exceed the total maximum load.

DON'T

Masterplug Help Line 03300 249 279

Supplied by Luceco PLC Stafford Park 1 Telford TF3 3BD ENGLAND

Visit our website at

www.masterplug.com