


Universal Charger

GAUGES BATTERY POWER



- Indicates amount of charge in the battery

ENSURES FULL CHARGE



- Charges batteries to 100% capacity

MAXIMIZES PERFORMANCE




- Helps batteries retain capacity by preventing damage from overcharge



VERSATILE

- Charges AA, AAA, C, D and 9V NiMH batteries



Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with *Energizer*® NiMH batteries.

EMEA Region

[Download Instructions \(multilingual\)](#)

Product Detail:

Designation: Universal Charger

Color: Black

Charging Current: 2 or 4 "AA-C-D" 650mA
2 or 4 "AAA" 400mA
1 or 2 "9V" 17mA

Note: Batteries must be charged in pairs with the exception of "9V" batteries that can be charged individually

Charging Times: (estimated)	Battery (NiMH)	Capacity (mAh)	Estimated (time)
	AA	1300-2000	3-4 hrs
	AA	2000-2400	4-5 hrs
	AAA	500-800	2-3 hrs
	C/D	2500	4 hrs
	9V	175	11 hrs

Shutoff Mechanism: Delta V Detection: 5mV per cell for "AA-AAA-C-D"
Timer Control: 2 or 4 "AA-C-D" 5 hours
2 or 4 "AA" 3.5 hours

AC Adapter Input: 100-240VAC, 50/60Hz, 8W

AC Adapter Output: 12VDC, 600mA

Trickle Charge: "AA-C-D" 50mA
"AAA" 25mA

Typical Weight: 322 grams

Dimensions (mm): 65 x 180 x 130 (H x L x W)

Safety Features: Short Circuit and Reverse Polarity Protection
Primary Battery Detection
Bad Battery Detection
Delta V Charging Cut Off
Safety Timer to Prevent Overcharge

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

©2017 Energizer Brands, LLC

Contents herein do not constitute a warranty.